The Geiger Counter

Andrew Mark Allen - 05370299

March 3, 2012

Abstract

In this experiment, a Geiger counter, an amplifier and bias unit, and a counting unit were used to measure the half-life of a sample of radioactive Iridium, and two C^{14} samples were used to measure the dead-time of the Geiger Counter.

Aims

- To determine the half-life of an irradiated sample of indium.
- To determine the dead-time of the Geiger counter.

Introduction and Theory

Radioactive Decay

The spontaneous decay of radioactive atoms is given by the equation

$$\frac{dN}{dt} = \lambda N$$

where N is the number of undecayed nuclei and λ is a constant parameter called the decay constant. Solving this equation for N gives us

$$N(t) = N_0 e^{-\lambda t}$$

where N_0 is the number of nuclei present at time $t = 0$. This describes an exponential decay, and since the rate $R \propto N(t)$,

$$\log R \propto -\lambda$$

The half life of a radioactive sample, that is, the time for which it takes a radioactive sample to decay to the point where only half as many of the original radioactive atoms are present, is given by the formula

$$t_{1/2} = \frac{\ln 2}{\lambda}$$

The Geiger Counter

A Geiger counter is a device that measures ionising radiation. It consists of a tube, the Geiger-Müller Tube (GM Tube), filled with an inert gas such as Argon at low pressure. The tube is connected to an electric circuit such that the surface acts as a cathode while a central wire acts as an anode (see diagram). The tube is open on one end but for a thin mica window, which is thin enough to allow alpha particles along with beta and gamma radiation through.

When a photon or particle enters the tube it ionises some of the particles of gas so that the resulting ions and free electrons are accelerated towards the anode and cathode respectively. On the way they will cause collisions with more particles creating further ionisations, with the resulting cascade referred to as an *electron avalanche*. The resulting pulse of electricity can be amplified by the electric circuit to create an audible pulse, or can be counted with an electronic circuit.

However, there is not a one to one correspondence between the interactions in the tube and the resulting pulses. There is a period of time between a gas particle being hit by radiation and the count being registered during which any additional interactions will not be recorded as additional counts. This time period is called the *dead time*. The effect of this dead time becomes more pronounced as the count rate increases.

Calculating Dead Time

The dead time for the GM Tube can be calculated if one has two samples of radioactive sources, by recording the individual count rates and the combined count rate, as described here. To avoid confusion, n will always refer to the *true count rate*, i.e. what would be recorded if the dead time of the tube was zero, while m variables refer to the *measured count rate*, a number in all instances read off the machine. A combined rate refers to the rate corresponding to the situation where the Geiger counter is exposed to the two sources at the same time.

Let n_1 and n_2 stand for the true count rates of each of the two radioactive sources, and let $n = n_1 + n_2$ be the combined count rate. Let τ be the dead time, and let m_1 and m_2 be the measured count rates, with the combined measured count rate $m \neq m_1 + m_2$.

It should be seen that during a measurement $m\tau$ is the total dead time, and thus $nm\tau$ are the number of readings lost during this time. Then,

$$n_1 = m_1 + n_1 m_1 \tau$$

or rearranging,

$$n_1 = \frac{m_1}{1 - m_1\tau}$$

Since $n = n_1 + n_2$,

$$\frac{m_1}{1 - m_1\tau} + \frac{m_2}{1 - m_2\tau} = \frac{m}{1 - m\tau}$$

Cross-multiplying and cancelling terms gives us

$$mm_1m_2\tau^2 - 2m_1m_2\tau + (m_1 + m_2 + m)$$

and solving this quadratic gives us the equation for the dead time:

When measuring

Experimental Method

Results and Analysis

Discussion and Conclusion